

2550 Gray Falls Dr., Suite#128, Houston, TX, 77077 TEL: 1-281-870-8822 EMAIL: Sales@DynamicEng.com

#### **Features and Benefits**

Ultra-High Stability (UHS) ±100 ppb Less than 0.1 ppb Allan deviation

#### **Typical Applications**


Global Navigation Satellite Systems Small cell mobile communications such as WCDMA, TD-SCDMA, CMDA2000, WiMax, and LTE cell systems standards


#### **Description**


State-of-the-art next generation compensation IC technology used in conjunction with precision resonator design and processing techniques


#### **Mechanical Drawing & Pin Connections**











Pin function #1 Vc (EFC) #5 GND #6 Output #9 E/D or NC

#10 Vcc

Do not connect #2, #3, #4, #7, #8



2550 Gray Falls Dr., Suite#128, Houston, TX, 77077 TEL: 1-281-870-8822 EMAIL: Sales@DynamicEng.com

# **Specifications**

Oscillator Specification	Condition	Value Typ.	Unit	
Nominal Frequency		20.00	MHz	
Frequency Stability		_0.00		
Frequency Tolerance ex. Factory	@ +25°C	0.0~1.0	ppm	
VS. Temperature reference (F <sub>MAX</sub> + F <sub>MIN</sub> ) / 2	Over -40°C to +85°C	≤ ±0.10	ppm	
VS ±5% change in supply voltage	Reference to frequency at nominal supply	≤±0.05	ppm	
VS. ±10% change in load	Reference to frequency at nominal load	≤ <u>+</u> 0.05	ppm	
VS. Aging	1 <sup>st</sup> year 10 years	≤±1.00 ≤ ±3.50	ppm	
Frequency slope	Over operating temperature	≤0.05	ppm/°C	
Short term stability ADEV	t = 1 sec	< 1 x 10 <sup>-10</sup>	· ·	
RF Output				
Output Wave Form		Clipped Sine wave		
Output Level		>0.8	Vp-p	
Output Load	±10%	10 kΩ//15pF		
Power Supply				
Supply Voltage		+3.3	V	
Current Consumption		<5	mA	
Frequency Control and Phase No	pise			
Electronic frequency control (EFC) Range		ΔF > ±5	ppm	
Control Voltage (V <sub>c</sub> )	±1.0V Positive slope	+1.5	V	
EFC Input Impedance		> 100	kΩ	
Start Up Time		< 2	ms	
Tri-State Function	Pin #6> oscillation Pin #6> high impedance	Pin #9 Pin #9	high or open low	
Phase Noise @ 20.0 MHz	@ 100 Hz @ 1 kHz @ 10 kHz @ 100 kHz	< -120 < -145 <-155 <-155	dBc/Hz	
Environmental Conditions				
Operating temperature range		-40 to +85	°C	
Storage temperature range		-55 to +125	°C	
Moisture Sensitivity	Unlimited	Level 1		
Reflow profiles as per IPC / JEDEC J-STD-020	Over 10 seconds max	≤ 260 max	°C	



2550 Gray Falls Dr., Suite#128, Houston, TX, 77077 TEL: 1-281-870-8822 EMAIL: Sales@DynamicEng.com

### **Environmental Conditions**

Test	IEC 60068 Part	IEC 60679-1 Clause	MIL-STD-202G Method	MIL-STD-810F Method	MIL-PRF-55310D Clause	Test Conditions (IEC)
Sealing Tests (if applicable)	2-17	5.6.2	112E		3.6.1.2	Gross lead: Test Oc Fine Leak: Test Qk
Solderability	2-20	5.6.3	208H		3.6.52	Test Ta, Method 1
Resistance to soldering heat	2-58		210F		3.6.48	Test Td <sub>1</sub> , Method 2 Test Td <sub>2</sub> , Method 2
Shock	2-27	5.6.8	213B	516.4	3.6.40	Test Ea, 3 x per axes 100g, 6ms half-sine pulse
Vibration sinusoidal	2-6	5.6.7.1	201A 204D	516.4-4	3.6.38.1 3.6.38.2	Test F <sub>C</sub> , 30 min per axes 10 Hz – 55 Hz, 0, 75 mm, 55 Hz – 2 kHz, 10 g
Vibration random	2-64	5.6.7.3	214A	514.5	3.6.38.3 3.6.38.4	Test Fdb
Endurance Tests - Aging - Extended aging		5.7.1 5.7.2	108A		4.8.35	30 days @ 85°C 1000 h, 2000 h, 8000h @ 85°C

#### **Handling Precautions**

#### Flux Residue Resistance

Analog circuit performance can be affected by unclean board.

Be aware if the circuit has very high resistances – even in the low  $M\Omega$  – special attention may need to be paid to cleaning. A finished assembly may be adversely affected by flux or cleansing residue. The electronics industry in the past few years has joined the rest of the world in becoming environmentally responsible. Hazardous chemicals are being removed from the manufacturing process – including flux that has to be cleaned with organic solvents. Water-soluble fluxes are becoming more common, but water itself can become contaminated easily with impurities. These impurities will lower the insulation characteristics of the PCB substrate. It is vitally important to clean with freshly distilled water every time a high-impedance circuit is cleaned. There are applications that may call for the older organic fluxes and solvents, such as very low power battery powered equipment with resistors in the 10s of M $\Omega$  range. Nothing can beat a good vapor defluxing machine for ensuring that the board is clean.



2550 Gray Falls Dr., Suite#128, Houston, TX, 77077 TEL: 1-281-870-8822 EMAIL: Sales@DynamicEng.com

# **Test Circuit**

