



**SUMMARY TEST DATA
ON
PTRAN-CC-100M18G-70-MAH**

PL19636/1629

Customer: _____	Tested By: RLCombs
SO No: _____	Temperature: +25°C
Model No: PTRAN-CC-100M18G-70-MAH	Date: 9/16/2016
Serial No: PL19636/1629	Drawing No: 27624305 Rev: A1

TEST ITEM NO:	PARAMETERS	SPECIFIED VALUE	MEASURED VALUE	REMARKS QA/QC
1	J2 Input Frequency (RF RX Input)	100MHz-18.0GHz	100MHz-18.0GHz	
2	J2 Input Power Level	-62dBm to +8dBm Typical	-62dBm to +8dBm	
3	J4A Input Frequency (IF1 Input)	100MHz-4GHz	100MHz-4GHz	
4	J4A Input Power Level	0dBm Typ.	0dBm	
5	J4B Input Frequency (IF2 Input)	100MHz-4GHz	100MHz-4GHz	
6	J4B Input Power Level	0dBm Typ.	0dBm	
7	J9 Input Frequency (LO1 Input)	4GHz-20GHz	4GHz-20GHz	
8	J9 Input Power Level	+10dBm Typ.	+10dBm	
9	J10 Input Frequency (LO2 Input)	4GHz-20GHz	4GHz-20GHz	
10	J10 Input Power Level	+10dBm Typ.	+10dBm	
11	J3A Output Frequency (IF1 Output)	100MHz-4GHz	100MHz-4GHz	
12	J3A Output Power Level	0dBm Typ. for Limited SDLVA Ch	+0.9dBm	
13	J3B Output Frequency (IF2 Output)	100MHz-4GHz	100MHz-4GHz	
14	J3B Output Power Level	0dBm Typ. for Limited SDLVA Ch	+0.8dBm	
15	J5 Output Frequency (RF Transmit Output)	100MHz-18GHz	100MHz-18GHz	
16	J5 Output Power Level	-20dBm to -15dBm Typ. for 0 dB Attenuation	-27.5dBm	

7311-F Grove Road Frederick, MD 21704 USA Phone: (301)662-5019 Fax: (301)662-1731
Email: sales@pmi-rf.com



**SUMMARY TEST DATA
ON
PTRAN-CC-100M18G-70-MAH**

PL19636/1629

17	J7 Output Frequency (RF Transmit BIT Output)	100MHz-18GHz	100MHz- 18GHz	
18	J7 Output Power Level	-20dBm to -15dBm Typ. for 0 dB Attenuation	-26.3dBm	
19	Attenuation Range	0 to 31 dB Attenuation in 1 dB Typ. steps	31dB	
20	J8 Output Frequency (TX Sample Output)	100MHz-18GHz	100MHz- 18GHz	
21	J8 Output Power Level	-40dBm to -30dBm Typ.	-33 to -37dBm	
22	Power Supply	+12V @ 2A Typ. +5V @ 1.5A Typ. +3.3V @ 0.5A Typ. -12V @ 1A Typ.	+12V @ 0.61A +5V @ 0.59A +3.3V @ 0.01A -12V @ 0.74A	
23	SDLVA Data Attached	SDLVA-100M18G-CW-70-MAH Serial Number 19630		

QA/QC Approval: _____ Date: _____